

2-CHANNEL PREAMPLIFIER WITH ALC

The LA3225T,3226T are 2-channel low-noise preamplifiers designed for cassette tape recorder use.

The LA3225T, 3226T contain preamplifiers and rectifiers in a 10-pin single-end package and require fewer number of external parts.

Use

- . Stereo, compact cassette tape recorders (recording/playback), radio-cassette recorders (recording/playback).
- . LA3225T: 6V-operated tape recorder use
- . LA3226T: 9V-operated tape recorder use

Features


- Open loop gain 85dB typ.
- On-chip rectifiers and ALC circuit.
- Capable of operating from $V_{CC}=3.8V$ (LA3225T), $V_{CC}=5.5V$ (LA3226T) because of good reduced voltage characteristic
- On-chip feedback resistors ($R_{NF}=100k\Omega$)
- The rectifier operation can be stopped at the playback mode (ALC OFF).

Maximum Ratings at Ta=25°C

Maximum Ratings at Ta=25°C			unit
Maximum Supply Voltage	V _{CC} max	14.0	V
Allowable Power Dissipation	P _d max Ta≤40°C	730	mW
Operating Temperature	T _{opg}	-20 to +75	°C
Storage Temperature	T _{stg}	-40 to +125	°C


Operating Conditions at $T_a = 25^\circ\text{C}$

Operating Conditions at Ta=25°C			unit
Operating Voltage Range	V _{CC} op	LA3225T	3.8 to 12.0 V
		LA3226T	5.5 to 12.0 V



The application circuit diagrams and circuit constants herein are included as an example and provide no guarantee for designing equipment to be mass-produced. The information herein is believed to be accurate and reliable. However, no responsibility is assumed by SANYO for its use, nor for any infringements of patents or other rights of third parties which may result from its use.

Case Outline 3043A-S10IC
(unit:mm)



Specifications and information herein are subject to change without notice.

SANYO: SEP 10

SANYO Electric Co., Ltd. Semiconductor Overseas Marketing Div.
15-13, 6 chome, Sotokanda, Chiyoda-ku, TOKYO 101 JAPAN


0137KI/7036KI, TS No. 2179-1/2

LA3225T.3226T


Operating Characteristics at $T_a=25^{\circ}\text{C}$, $V_{CC}=5.0\text{V}$ (LA3225T), $V_{CC}=6.0\text{V}$ (LA3226T),
 $R_L=10\text{k}\Omega$, $f=1\text{kHz}$, $0\text{dB}=0.775\text{V}$

			min	typ	max	unit
Quiescent Current	I_{COO}	$R_g=2.2\text{k}\Omega$		6.0	12	mA
[Amp Section]						
Voltage Gain (Open Loop)	V_{G_O}	$V_o=0\text{dB}$	80	85		dB
(Closed Loop)	V_{G_R}	$V_o=-10\text{dB}$, flat	57	60	63	dB
	V_{G_P}	$V_o=-10\text{dB}$, NAB	42	45	48	dB
Total Harmonic Distortion	THD	$V_o=0\text{dB}$, NAB		0.15	1.0	%
Maximum Output Voltage	$V_{o\text{ max}}$	THD=1%	0.7	0.85		V
Equivalent Input Noise Voltage	V_{NIR}	$R_g=2.2\text{k}\Omega$, $V_G=60\text{dB}/1\text{kHz}$, flat		1.0	2.0	μV
	V_{NIP}	$R_g=2.2\text{k}\Omega$, $V_G=45\text{dB}/1\text{kHz}$, NAB		0.9	1.8	μV
Input Resistance	r_i		21	30		$\text{k}\Omega$
Channel Separation	Sep	$V_G=45/1\text{kHz}$, NAB	40	51		dB
[ALC Section]						
ALC Range	ALC W	Input range for ALC output difference of +3dB, flat	35	45		dB
ALC Balance	ALC B	V_o ratio of ch1/ch2 at $V_i=-50\text{dB}$, flat			2	dB
ALC Distortion	ALC THD	$V_i=-50\text{dB}$, flat		0.8	2.0	%
ALC Output Voltage	ALC v_o	LA3225T	0.36	0.45	0.53	V
		LA3226T	0.75	0.85	0.95	V

Equivalent Circuit Block Diagram



Sample Application Circuit



- ※ : . The recording gain and playback gain are set to 60dB and 45dB respectively.
- . The input coupling capacitor for the amplifier is required to prevent the noise that may occur at the time of R/P select.